

## 38149 MAH PRO SENSOR C

Accessory for dust-proof light fittings

5905339381491



Kanlux MAH PRO hermetic luminaires can be equipped with a motion sensor (38144 MAH PRO SENSOR) ensuring reliable motion detection and having a master-slave function (i.e. the first or the first and last luminaire turns the entire light line on and off).

### GENERAL DATA:

**Place of application:** Indoors

**Sensitivity regulation:** yes

### TECHNICAL DATA:

**Rated voltage [V]:** 220-240 AC

**Rated frequency [Hz]:** 50

**Class of protection against electric shock:** II

**Sensor type:** microwave

**Sensor-operation time [second-minute]:** 5/30/90-5/20/30

**Sensor-operation frequency [MHz]:** 5800

**Maximum operating time [min]:** 30

**Minimum operating time[s]:** 5

**Maximum power [VA]:** max 400

**Illumination-level setpoint by which the sensor detects movement [lx]:** 2/10/30/50/disable

**IP class:** 20

**Sensor range[m]:** max 6

### LOGISTIC DATA:

**Unit of measurement:** unit

**Packaging method:** 100

**Number of units in the secondary packaging:** 1

**Number of units in the packaging:** 100

**Net unit weight [g]:** 84

**Grammage [g]:** 114.5

**Gross unit weight [g]:** 108

**Length of a unit pack [cm]:** 23

**Width of a unit pack [cm]:** 4

**Height of a unit pack [cm]:** 3.5

**Weight of a cardboard box [kg]:** 11.45

**Width of a cardboard box [cm]:** 44.5

**Height of a cardboard box [cm]:** 21

**Length of a cardboard box [cm]:** 47.5

## 38149 MAH PRO SENSOR C

---

Accessory for dust-proof light fittings

Volume of a cardboard box [m<sup>3</sup>] : 0.044389

### ADDITIONAL INFORMATION:

- 5 years Warranty under the terms of the warranty statement, available on our website