

08910 MARID JQ-L

PIR motion sensor




[V] 220-240 AC	[Hz] 50/60	[VA] 40-500	IP 20			
F	[m] max 12	[°] H150/V30	[s] - [min] 10-7	PIR	[lx] 3-2000	[°C] 5÷25
	[mm] 0.75÷2.5					



MARID JQ-L **08910** 40-500 Recessed mount in the wall H150/V30 10-7 PIR

Kanlux MARID JQ is a motion detector whose maximum detection range comes to 12 metres. You can set adjustments of the lighting time and light intensity level at which the detector works. The detector can be activated by means of sound signal too.

- Maximum movement detection up to 12m
- Maximum horizontal angle of operation of the motion sensor - 150°
- Maximum vertical angle of operation of the motion sensor - 30°
- Light on time adjustable from 10s to 7min
- Capability to set the light intensity of the environment in which the device works
- Motion detection 0.3...3m/s (1...10km/h)
- Sensitivity adjustment in the range of 3...1000lx
- Capability to activate the sensor with a 30-90db sound signal
- Designed only for resistive loads
- Material: plastic



08910 MARID JQ-L

PIR motion sensor

MARID JQ-L

