

## FUTURIO LED 37W 1180mm

Luminaire étanche LED



[V] 220-240 AC	[Hz] 50	$\geq 30000$	50000	ellipse $\leq 3^\circ$ MacAdam	Ra 80	SMD
		<b>IP</b> 65			<b>IK</b> 08	
[mm] 1,5+2,5	m 0,5m	<b>CE</b>	<b>EAC</b>	<b>PZH</b>	<b>UK</b> <b>CA</b>	



### FT1200 37W-840-OPL

	[W]	Tc [K]	TYPE	[°]	[lm]	lm/W	[mm]	[°C]	
FT1200 37W-840-OPL	<b>28630</b>	37	4000	opal	X130/Y110	5000	135	1180	-25÷40
FT1200 37W-840-RYF	<b>28631</b>	37	4000	rainurée	X115/Y105	5400	146	1180	-25÷40
FT1200 37W-840-INT	<b>28633</b>	37	4000	prismatique, faisceau intensif	X70/Y95	5200	141	1180	-25÷40
FT1200 37W-840-ASY	<b>28634</b>	37	4000	prismatique, asymétrique	X75/Y95	5200	141	1180	-25÷40

- Matériau du boîtier: PC
- Matériau du diffuseur: PC



FT1200 37W-840-OPL



FT1200 37W-840-RYF




FT1200 37W-840-INT




FT1200 37W-840-ASY

## FUTURIO LED 37W 1180mm


Luminaire étanche LED




FT1200 37W-840-OPL



FT1200 37W-840-RYF



FT1200 37W-840-INT



FT1200 37W-840-ASY