


34940 S SENSOR PIR INT 10M

PIR motion sensor

5905339349408



S SENSOR PIR INT 10M



Motion detection sensor for indoor use. By pairing it in the app with selected SMART devices, it will not only turn on the light when motion is detected but it will also trigger any programmed action - depending on the SMART devices paired and the function assigned to them. The sensor is battery powered but it can also be charged via USB. An alarm will let you know when the battery is low. Learn more about Kanlux SMART at www.kanluxsmart.com.

PRODUCT PARAMETERS:

Colour: white

Place of assembly: ceiling mounted, wall mounted, surface mounted

Place of application: Indoors

Control: Wi-Fi 2,4 GHz

Alarm dźwiękowy o niskim poziomie baterii: yes

Batteries included: no

Sensitivity regulation: yes

Battery-power supply: yes

Battery-power supply: 2 x CR123A

Rated voltage [V]: 2 x 3V DC / 5V USB

Class of protection against electric shock: III

Ambient temperature range to which the product can be exposed: -10+40

Sensor type: PIR

sensor working angle [°]: 120

IP class: 20

Sensor range[m]: 8

LOGISTIC DATA:

Unit of measurement: unit

Packaging method: 125

Number of units in the secondary packaging: 1

Number of units in the packaging: 125

Net unit weight [g]: 54

Grammage [g]: 82.4

Length of a unit pack [cm]: 6.5

Width of a unit pack [cm]: 6.5

Height of a unit pack [cm]: 8.5

Weight of a cardboard box [kg]: 10.3

Width of a cardboard box [cm]: 33.5

Height of a cardboard box [cm]: 33

Length of a cardboard box [cm]: 45

Volume of a cardboard box [m³]: 0.049748