

KRO10

Residual-current circuit breaker with overcurrent module, 10kA, 2P



[V]

230 AC

[Hz]

50

(mm²)

10÷16

°C

-25÷40

IP

20

Icn [A]

10000

2

2P

2

TH 35

Ui [V]

400

CE

EAC

UK
CA

KRO10-2/B10/30

			In [A]	IΔn [mA]	Residual-current protection type
KRO10-2/B10/30	32882	B	10	30	AC
KRO10-2/B10/30-A	32883	B	10	30	A
KRO10-2/B16/30	32884	B	16	30	AC
KRO10-2/B16/30-A	32885	B	16	30	A
KRO10-2/B20/30	32886	B	20	30	AC
KRO10-2/B25/30	32887	B	25	30	AC
KRO10-2/B6/30	32888	B	6	30	AC
KRO10-2/C10/30	32889	C	10	30	AC
KRO10-2/C10/30-A	32890	C	10	30	A
KRO10-2/C16/30	32891	C	16	30	AC
KRO10-2/B20/30-A	39310	B	20	30	A
KRO10-2/C20/30	39311	C	20	30	AC
KRO10-2/C20/30-A	39312	C	20	30	A
KRO10-2/C25/30	39313	C	25	30	AC
KRO10-2/C25/30-A	39314	C	25	30	A
KRO10-2/C32/30	39315	C	32	30	AC
KRO10-2/C32/30-A	39316	C	32	30	A

KRO10

Residual-current circuit breaker with overcurrent module, 10kA, 2P



KRO10-2/B10/30



KRO10-2/B10/30-A



KRO10-2/B16/30



KRO10-2/B16/30-A



KRO10-2/B20/30



KRO10-2/B25/30



KRO10-2/B6/30



KRO10-2/C10/30



KRO10-2/C10/30-A



KRO10-2/C16/30



KRO10-2/B20/30-A



KRO10-2/C20/30

KRO10

Residual-current circuit breaker with overcurrent module, 10kA, 2P



KRO10-2/C20/30-A



KRO10-2/C25/30




KRO10-2/C25/30-A




KRO10-2/C32/30




KRO10-2/C32/30-A




KRO10-2/B10/30



KRO10-2/B10/30-A




KRO10-2/B16/30




KRO10-2/B16/30-A

KRO10


Residual-current circuit breaker with overcurrent module, 10kA, 2P




KRO10-2/B20/30




KRO10-2/B25/30




KRO10-2/B6/30




KRO10-2/C10/30




KRO10-2/C10/30-A




KRO10-2/C16/30




KRO10-2/B20/30-A




KRO10-2/C20/30




KRO10-2/C20/30-A



KRO10-2/C25/30




KRO10-2/C25/30-A



KRO10-2/C32/30

KRO10

Residual-current circuit breaker with overcurrent module, 10kA, 2P



KRO10-2/C32/30-A