

## AL-LL-NT

### Luminaire profilés linéaire LED



[V] 220-240 AC	[Hz] 50	≥30000	[h] 50000	ellipse ≤3x MacAdam	Ra 80	SMD
		IP 20		[°C] 5÷25		
[mm²] 1,5÷2,5		0,5m				



### AL-LL-NW-MAT-W-NT

	[W]	Tc [K]		TYPE	[°]		[m]	[mm]
AL-LL-NW-MAT-W-NT	<b>34080</b>	33	4000	mat	X85/Y95	blanc	4550	1700
AL-LL-WW-MAT-W-NT	<b>34082</b>	33	3000	mat	X85/Y95	blanc	4100	1700
AL-LL-NW-MPR-W-NT	<b>34084</b>	33	4000	microprismatique	X75/Y90	blanc	4150	1700
AL-LL-WW-MPR-W-NT	<b>34086</b>	33	3000	microprismatique	X75/Y90	blanc	3750	1700
AL-LL-NW-MAT-B-NT	<b>34092</b>	33	4000	mat	X85/Y95	noir	4550	1700
AL-LL-WW-MAT-B-NT	<b>34094</b>	33	3000	mat	X85/Y95	noir	4100	1700
AL-LL-NW-MPR-B-NT	<b>34096</b>	33	4000	microprismatique	X75/Y90	noir	4150	1700
AL-LL-WW-MPR-B-NT	<b>34098</b>	33	3000	microprismatique	X75/Y90	noir	3750	1700
AL-LL-NW-MAT-S-NT	<b>34104</b>	33	4000	mat	X85/Y95	argent	4550	1700
AL-LL-WW-MAT-S-NT	<b>34106</b>	33	3000	mat	X85/Y95	argent	4100	1700
AL-LL-NW-MPR-S-NT	<b>34108</b>	33	4000	microprismatique	X75/Y90	argent	4150	1700
AL-LL-WW-MPR-S-NT	<b>34110</b>	33	3000	microprismatique	X75/Y90	argent	3750	1700
AL-LLAS-NW-MAT-W-NT	<b>34408</b>	33	4000	asymétrique	X85/Y95	blanc	4550	1700

- Une garantie de 5 ans accordée conformément aux termes de la déclaration de garantie disponible sur le site d'Internet
- Matériau du boîtier: alliage en aluminium
- Matériau du diffuseur: matériau plastique

## AL-LL-NT

Luminaire profilés linéaire LED



AL-LL-NW-MAT-W-NT



AL-LL-WW-MAT-W-NT



AL-LL-NW-MPR-W-NT



AL-LL-WW-MPR-W-NT



AL-LL-NW-MAT-B-NT



AL-LL-WW-MAT-B-NT



AL-LL-NW-MPR-B-NT



AL-LL-WW-MPR-B-NT



AL-LL-NW-MAT-S-NT



AL-LL-WW-MAT-S-NT



AL-LL-NW-MPR-S-NT



AL-LL-WW-MPR-S-NT

Date of issue: 01.03.2023, 12:57

Nous nous réservons le droit d'apporter toute modification technique sans information préalable. Les données de ce contenu ne sont pas juridiquement contraignantes.


## AL-LL-NT

---

Luminaire profilés linéaire LED



AL-LLAS-NW-MAT-W-NT



AL-LL-NT

## AL-LL-NT

---

### Luminaire profilés linéaire LED

#### Accessoires

<b>32540</b>	ALIN CORD 1F-W	Power supply terminal for ALIN luminaires and tracks, 1-phase, white, 150 cm
		
<b>32541</b>	ALIN CORD 1F-B	Power supply terminal for ALIN luminaires and tracks, 1-phase, black, 150 cm
		
<b>32542</b>	ALIN CORD 1F-SR	Power supply terminal for ALIN luminaires and tracks, 1-phase, silver 150 cm
		
<b>07871</b>	ROPE-NT 150 SINGLE	ROPE-NT 150 SINGLE câble en acier (unique) pour la suspension de luminaires, ensemble de 2 pièces
		
<b>29557</b>	ALIN NT GRIP	Wall bracket for the ALIN luminaire, 2 pcs included
		