


33701 S AD GN SCH 10A PM

Socket adaptor

5905339337016



Thanks to the Shucko socket adaptor, you can control (on/off function) devices without SMART functions (e.g.: an iron). We can also set a sequence of actions of our choice. The basic function is on/off, but the adaptor also has a built-in clock (weekly clock with a calendar), random functions and a timer/countdown function. This allows you to program different devices to turn on and off at specific times, even when you are not at home. In addition, the adaptor has a function to measure the energy consumption (of the device connected to it). Learn more about Kanlux SMART at www.kanluxsmart.com.

GENERAL DATA:

Colour: white

Place of assembly: power outlet

Place of application: Indoors

Control: Wi-Fi 2,4 GHz

TECHNICAL DATA:

Rated voltage [V]: 220-240 AC

Rated current [A]: 10

Class of protection against electric shock: I

Earthing type: type F

IP class: 20

LOGISTIC DATA:

Packaging method: 12

Number of units in the secondary packaging: 12

Number of units in the packaging: 144

Net unit weight [g]: 98

Grammage [g]: 141.53

Length of a unit pack [cm]: 7

Width of a unit pack [cm]: 6

Height of a unit pack [cm]: 8.5

Weight of a cardboard box [kg]: 20.38032

Width of a cardboard box [cm]: 40.5

Height of a cardboard box [cm]: 48

Length of a cardboard box [cm]: 47

Volume of a cardboard box [m³]: 0.091368