


33701 S AD GN SCH 10A PM

Socket adaptor

5905339337016



Thanks to the Shucko socket adapter, you can control (on/off function) devices without SMART functions (e.g.: an iron). We can also set a sequence of actions of our choice. The basic function is on/off, but the adapter also has a built-in clock (weekly clock with a calendar), random functions and a timer/countdown function. This allows you to program different devices to turn on and off at specific times, even when you are not at home. In addition, the adapter has a function to measure the energy consumption (of the device connected to it). Learn more about Kanlux SMART at www.kanluxsmart.com.

PRODUCT PARAMETERS:

Colour: white
Place of assembly: power outlet
Place of application: Indoors
Control: Wi-Fi 2,4 GHz
Rated voltage [V]: 220-240 AC
Rated current [A]: 10
Class of protection against electric shock: I
Earthing type: type F
IP class: 20

LOGISTIC DATA:

Packaging method: 12
Number of units in the secondary packaging: 12
Number of units in the packaging: 144
Net unit weight [g]: 98
Grammage [g]: 141.53
Length of a unit pack [cm]: 7
Width of a unit pack [cm]: 6
Height of a unit pack [cm]: 8.5
Weight of a cardboard box [kg]: 20.38032
Width of a cardboard box [cm]: 40.5
Height of a cardboard box [cm]: 48
Length of a cardboard box [cm]: 47
Volume of a cardboard box [m³]: 0.091368